

Servo Controlled Voltage Stabilizers

(Oil Cooled 3 - 3500 KVA)



Features & Benefits

- No potentiometer adjustments
- All parameters can be modified using the keypad in the front panel
- Set input voltage band
- Set output voltage
- Set output voltage sensitivity
- Output over / Under voltage cut-off
- Input over voltage / Under cut-off
- Over load cut-off
- Trip time delay adjustments with variable setting
- Manual and auto start facility
- Output start and stop facility

Technical Specification
Servo Controlled Voltage Stabilizers

Oil Cooled 3 KVA - 3500 KVA

Oil Cooled Servo Control Voltage Stabilizers		
Capacity	3-3500 KVA	
Input Voltage Range *	A) Range 1: 295 V-465 V	B) Range 2: 340 V-480 V
Output Voltage Range *	380/400/415 V +1% Set	
Input Frequency	47-53 Hz	
Control Type	Digital-Micro controller based	
Correction Speed*	70 V per second	
Reset	Manual / Auto Reset with time delay and programmable	
Protections	A) Electronic over & under voltage trip with time delay for input & output B) Electronic overload protection and short circuit protection upto 30 KVA through MCB and the manual bypass is built in. Above 30 KVA MCB /MCCB is an Optional. C) Surge Arrester/RF suppressor (OPTIONAL) D) Phase reversal protection and cut off E) Single phase prevention and cut off F) Neutral failure protection G) Frequency cut off protection H) Earth neutral voltage cut off protection	
Metering Digital Type (Class 1 Accuracy with Full Scale ± 1)	A) Input phase to neutral C) Output phase to neutral E) Load Current in all the phases	B) Input phase to phase D) Output phase to phase F) Frequency
Audio Alarm	For tripping conditions	
Nature of Cooling	ONAN	
Effect of Power Factor	Nil	
Waveform Distortion	Nil	
Annunciation Panel	Non Latching LED indications with dual colour for Over load Latching Conditions	
Efficiency	> 98%	
Cabinet Colour	Siemens Grey	
Provision of Cabling	Input and Output terminations with provisions for fixing cable glands	
Servo Motor Drive	Rugged AC step synchronous motor	
Operating Temperature	0-45°C	

* Range can be customised to customer requirement

♦ All specifications are subject to change

♦ Custom models available on request

Fuji Electric Consul Neowatt Pvt. Ltd.

(CIN:U31900TN1985PTCO11866)

 119, 120, 120A, Electrical and Electronics Industrial Estate,
 Perungudi, Chennai - 600 096, Tamil Nadu, India

☎ +91 78100 09955

 ✉ enquiry@consulneowatt.com

 ● www.india.fujielectric.com